NEXUS AMPLFIRE ST2350BC

Amplifier 350w

1 MIC input on front panel, 2 MIC/LINE inputs and 2 AUX inputs on rear panel
1 Pre-amp output, 1 group of Aux Send and Aux Return
CHIME and SIREN button
MIC1 input, Chime and Siren sound with priority function
MIC2 and MIC3 input with delay effect, inside effector with 3 knobs
Main volume adjuster, treble and bass adjusters
5-segment level indicator, signal, peak and fault indication
Mp3 player with Bluetooth and FM radio
Protection: over current, over heating, short-circuit, limiter, turn on delay and DC offset
6 zoning output with volume adjusters
Output: 100V, 70V, 4~16 ohm
Power supply: AC230V, DC24V(backup power)

